

Charging regulator

XTRA3210N-XDS3 BLE 30A

Product code: R0242

30A

Rated current

MPPT

Type



FUNCTIONS

- Optimizes charging by tracking the maximum power point, increasing the efficiency of the photovoltaic system.
- Ensures stable and safe operation, especially when using oversized photovoltaic modules.
- Protects the system from overheating by adjusting the output power according to working conditions.
- Increases charging efficiency by converting excess voltage into higher current.
- Enables real-time monitoring and management of the photovoltaic system.


4sun®

TECHNICAL DATA

INDEX	R0242
MODEL	XTRA3210N-XDS3 BLE 30A
Nominal system voltage	12/24VDC Auto
Battery type	Sealed/Gel/Flooded
Working voltage [V]	8~32
Rated charging current [A]	30
Rated discharge current [A]	30
Maximum PV circuit voltage [V]	100
Charging voltage [V]	14,6
Low-voltage cut-off voltage [V]	11,1
Connection voltage [V]	12,6
Own consumption	12V≤15mA; 24V≤9mA
Efficiency	≤95%, (N.C.)
Protection	IP33
Warranty	2 years
Equalisation voltage [V]	Sealed: 14,6
Dimensions (L x W x H) [mm]	228x165x60
Weight (g)	1300
Temperature range	-25°C~+50°C

APPLICATION


Solar Car




Solar Home




Solar Backpack



Solar Boat



Solar Street Light



Solar Power Generator

