

VOLTAGE CONVERTER

MAXX 2000W

Sinus 12VDC/230VAC
[1000W/2000W]



Pure Sinus

MAXX

TECHNICAL DATA

Model	MAXX 2000W Sinus 12VDC/230VAC
Product code	R0209
Continuous power	1000W
Momentary power	2000W (2s)
DC input voltage	10.8V-16V
AC output voltage	230V AC $\pm$ 5%
Discharge current less than	$\leq 0.6A$
Output frequency class	50Hz $\pm$ 0.5Hz
Output wave	Pure sinusoidal
USB	QC3.0
Low voltage alarm	11.2V
Protection against low voltage	10.8V
Protection against overvoltage	16V
Recovery after low voltage	12.4V
Recovery after high voltage	16V
Workingtemperature	-20° - +50°
Product dimensions (mm)	324x184x85
Net weight (kg)	2.96
Warranty	24 months
Mounting	4 mm ²
Cooling method	windmill