

VOLTAGE CONVERTER

MAXX 6000W

Sinus 12VDC/230VAC
[3000W/6000W]



Pure Sinus

MAXX

TECHNICAL DATA

Model	MAXX 6000W Sinus 12VDC/230VAC
Product code	R0276
Continuous power	3000W
Momentary power	6000W (2s)
DC input voltage	10.8V-16V
AC output voltage	230V AC±5%
Discharge current less than	≤0.9A
Output frequency class	50Hz±0.5Hz
Output wave	Pure sinusoidal
USB	QC3.0 18W
Low voltage alarm	11.2V
Protection against low voltage	10.8V
Protection against overvoltage	16V
Recovery after low voltage	12.4V
Recovery after high voltage	15.5V
Workingtemperature	-20°-+50°
Product dimensions (mm)	430×205×85
Net weight (kg)	5.42
Warranty	24 months
DC cable	35 mm ²
Cooling method	air cooling