

VOLTAGE CONVERTER

MAXX 1000W

Modified Sinus
12VDC/230VAC

[500W/1000W]



The modified sine wave inverter is a device that enables the conversion of voltage from 12V to 230V AC. Perfect for powering simple electrical appliances such as chargers, LED lights, fans or small household appliances.



Modified Sinus

MAXX

TECHNICAL DATA

Model	MAXX 4000W 12VDC/230VAC
Product code	R0277
Continuous power	500W
Momentary power	1000W
DC input voltage	10,8-16V
AC output voltage	230VAC±5%
Discharge current less than	≤0,2A
Output frequency class	50Hz±0.5Hz
Output wave	Modified sinusoidal
USB	QC3.0 18W
Low voltage alarm	11,2±0.5V
Protection against low voltage	10,8±0.5V
Protection against overvoltage	16±0.5V
Recovery after low voltage	12,4±0.5V
Recovery after high voltage	15,5±0.2V
Working temperature	-20°C +50°C
Product dimensions (mm)	216×107×63
Net weight (kg)	0,8
Max. output efficiency	88%
DC cable	6mm ²
Warranty	24 months
Cooling method	Intelligent air cooling