## VOLTAGE CONVERTER

## **UPS MAXX 2000W**



A UPS is a device that combines the functions of an inverter and a charger. When connected to an external power source, it automatically supplies equipment from the mains and simultaneously charges the battery.



**Pure Sinus** 



TECHNICAL DATA	
Model	UPS MAXX 2000W 12VDC/230VAC
Product code	R0279
Continuous power	1000W
Momentary power	2000W
DC input voltage	10,8-16V
AC output voltage	230VAC±5%
Discharge current less than	≤0,6A
Output frequency class	50Hz±0.5Hz
Output wave	Pure sinusoidal
USB	QC3.0 18W
Low voltage alarm	11,2±0.5V
Protection against low voltage	10,8±0.5V
Protection against overvoltage	16±0.5V
Recovery after low voltage	12,4±0,5V
Recovery after high voltage	15,5±0,2V
Max. Output Current	20A
Charging current	Max. 20A
Floating charge	13,8V
Charging voltage	14,8V
Working temperature	-10°C +50°C
Storage temperature	-30°C +70°C
Product dimensions (mm)	420×180×90
Net weight (kg)	4,12
Warranty	24 months
Cooling method	Intelligent air cooling

